

## JS8CALL FL WL NET Check-in Tips & Tricks.

1. In JS8CALL click in the upper frequency window (if you are not already on the 40m) select 7.078.
2. In the right-hand box (right click and select “Add Call or Group”
3. Add the following **@FLWLNET** and close.
4. To check for a direct, connect with N3MEL
  - a. In the lower center box type the following: **N3MEL SNR?** <enter>
  - b. If there is a direct link you should receive an SNR report back from N3MEL
5. If you receive a report back, then
  - a. In the same lower center box type the following: **N3MEL MSG YOUR NAME, YOUR TOWN, YOUR STATE** <enter>
  - b. If successful you should receive an **ACK** back from N3MEL
6. If Option one does not work, then try option number 2
  - a. Type the following in the lower center box: **@ALLCALL QUERY CALL N3MEL?** <enter>
  - b. If there are any stations that have heard N3MEL it will report back the **SNR** and **how long ago**. Look for the station with the best **SNR** and the most **recently heard time**.
  - c. Now in the lower center box type the call of the station you would like to relay through to N3MEL the syntax is: **W4AKH>N3MEL>YOUR NAME, YOUR TOWN, YOUR STATE** <enter> (Substitute W4AKH for the hearing station).
  - d. This check-in will take a little long to complete but you should receive an **ACK** back if successful.

Glenn/N3MEL